

Model Number 483C40	EIGHT-CHANNEL ICP®/VOLTAGE/CHARGE SENSOR SIGNAL CONDITIONER		Revision: G ECN #: 56201
Performance	ENGLISH	SI	OPTIONAL VERSIONS
Channels	8	8	Optional versions have identical specifications and accessories as listed for the standard model except where noted below. More than one option may be used.
Sensor Input Type(s)	ICP®, Voltage, Charge	ICP®, Voltage, Charge	
Gain(ICP®/ Voltage Input)	0.1 to 200	0.1 to 200	[4]
Gain(mV/pC)(Charge Input)	0.01 to 2000	0.01 to 2000	
Gain Increment(minimum)(ICP®/ Voltage Input)	0.1	0.1	[5]
Gain Increment(minimum)(Charge Input)	0.01	0.01	
Accuracy(ICP®/ Voltage Input)(Gain, 0.1 to 0.4)	± 5 %	± 5 %	[6]
Accuracy(ICP®/ Voltage Input)(Gain, 0.5 to 200)	± 1 %	± 1 %	
Accuracy(Charge Input)(Gain, 0.01 to 0.04)	± 6 %	± 6 %	
Accuracy(Charge Input)(Gain, 0.05 to 2000)	± 1 %	± 1 %	
Input Range(maximum)(Charge Input)	100,000 pC pk	100,000 pC pk	
Input Range(maximum)(ICP® Input)	10 Vpk	10 Vpk	
Input Range(maximum)(Voltage Input)	± 5 Vpk	± 5 Vpk	
Low Frequency Response(-5 %)(ICP®/ Voltage Input)	≤ 0.05 Hz	≤ 0.05 Hz	
Low Frequency Response(-5 %)(Charge Input)	0.5 Hz	0.5 Hz	
Electrical Filter Roll-off	160 dB/decade	160 dB/decade	
Filter Type(8-pole Butterworth)	Low Pass	Low Pass	
High Frequency Response(-5%)(Gain from 0.01 to 99.9)	>100 kHz	>100 kHz	
High Frequency Response(-5%)(Gain from 100 to 2000)	>50 kHz	>50 kHz	[6]
Electrical Filter Corner Frequency(-10 %)	0.1-0.3-1-3-10-30 kHz	0.1-0.3-1-3-10-30 kHz	
Electrical Filter Pass Band Amplitude Accuracy	1 %	1 %	
Phase Response(at 1 kHz)	± 2 °	± 2 °	
Non-Linearity	1 %	1 %	
Cross Talk	<-72 dB	<-72 dB	
TEDS Sensor Support	Yes	Yes	
Fault/Bias Monitor LEDs	Open/Short/Overload	Open/Short/Overload	
Control Interface			NOTES: [1] Use T1.6A fuse. [2] User adjustable, factory set at 4 mA (± 1.0 mA). Each channel individually adjustable. [3] Typical. [4] Max input signal is dependant on sensor bias. [5] The low frequency tolerance is accurate within ±25% of the specified frequency. [6] The high frequency tolerance is accurate within ±5% of the specified frequency. [7] See PCB Declaration of Conformance PS024 for details.
Digital Control Interface	Ethernet	Ethernet	
Environmental			
Temperature Range(Operating)	+32 to +120 °F	0 to +50 °C	
Electrical			[1]
Power Required(direct input to unit)	AC Power	AC Power	
AC Power(47 to 63 Hz)	100 to 240 VAC	100 to 240 VAC	[1]
AC Power	≤ 0.7 Amps	≤ 0.7 Amps	
Excitation Voltage(To Sensor)	>24 VDC	>24 VDC	[2]
DC Offset	<50 mV	<50 mV	
Constant Current Excitation(To Sensor)	2 to 20 mA	2 to 20 mA	[2]
Output Voltage(minimum)	10 V	10 V	
Output Current(minimum)	10 mA	10 mA	[3]
Output Impedance	<50 Ohm	<50 Ohm	
Broadband Electrical Noise(1 to 10,000 Hz)(Gain x1)	50 µV/rms	50 µV/rms	[3]
Spectral Noise(1 Hz)	8 µV/√Hz	8 µV/√Hz	
Spectral Noise(10 Hz)	2 µV/√Hz	2 µV/√Hz	[3]
Spectral Noise(100 Hz)	0.7 µV/√Hz	0.7 µV/√Hz	
Spectral Noise(1 kHz)	0.7 µV/√Hz	0.7 µV/√Hz	[3]
Spectral Noise(10 kHz)	0.6 µV/√Hz	0.6 µV/√Hz	
Broadband Electrical Noise(1 to 10,000 kHz)(Gain x10)	75 µV rms	75 µV rms	[3]
Spectral Noise(1 Hz)	18 µV/√Hz	18 µV/√Hz	
Spectral Noise(10 Hz)	1.5 µV/√Hz	1.5 µV/√Hz	[3]
Spectral Noise(100 Hz)	1.0 µV/√Hz	1.0 µV/√Hz	
Spectral Noise(1 kHz)	1.0 µV/√Hz	1.0 µV/√Hz	[3]
Spectral Noise(10 kHz)	1.0 µV/√Hz	1.0 µV/√Hz	
Broadband Electrical Noise(1 to 10,000 Hz)(Gain x100)	350 µV rms	350 µV rms	[3]
Spectral Noise(1 Hz)	100 µV/√Hz	100 µV/√Hz	
Spectral Noise(10 Hz)	10 µV/√Hz	10 µV/√Hz	[3]
Spectral Noise(100 Hz)	6 µV/√Hz	6 µV/√Hz	
Spectral Noise(1 kHz)	5 µV/√Hz	5 µV/√Hz	[3]
Broadband Electrical Noise(1 to 10,000 Hz)(0.1 mV/pC)	52.0 µV/rms	52.0 µV/rms	
Spectral Noise(10 kHz)	5 µV/√Hz	5 µV/√Hz	[3]
Spectral Noise(1 Hz)	10.0 µV/√Hz	10.0 µV/√Hz	
Spectral Noise(10 Hz)	1.5 µV/√Hz	1.5 µV/√Hz	[3]
Spectral Noise(100 Hz)	0.6 µV/√Hz	0.6 µV/√Hz	
Spectral Noise(1 kHz)	0.6 µV/√Hz	0.6 µV/√Hz	[3]
Spectral Noise(10 kHz)	0.6 µV/√Hz	0.6 µV/√Hz	
Broadband Electrical Noise(1 to 10,000 Hz)(1.0 mV/pC)	52.0 µV/rms	52.0 µV/rms	[3]
Spectral Noise(1 Hz)	14.0 µV/√Hz	14.0 µV/√Hz	
Spectral Noise(10 Hz)	2.0 µV/√Hz	2.0 µV/√Hz	[3]
Spectral Noise(100 Hz)	0.7 µV/√Hz	0.7 µV/√Hz	
Spectral Noise(1 kHz)	0.7 µV/√Hz	0.7 µV/√Hz	[3]
Spectral Noise(10 kHz)	0.7 µV/√Hz	0.7 µV/√Hz	
Broadband Electrical Noise(1 to 10,000 Hz)(10.0 mV/pC)	56.0 µV/rms	56.0 µV/rms	[3]
Spectral Noise(1 Hz)	15.0 µV/√Hz	15.0 µV/√Hz	
Spectral Noise(10 Hz)	2.0 µV/√Hz	2.0 µV/√Hz	[3]
Spectral Noise(100 Hz)	0.6 µV/√Hz	0.6 µV/√Hz	
Spectral Noise(1 kHz)	0.6 µV/√Hz	0.6 µV/√Hz	[3]
Spectral Noise(10 kHz)	0.6 µV/√Hz	0.6 µV/√Hz	
Oscillator(+/- 2%)(Internal Generator - ICP®/ Voltage Mode)	0.1 V pk	0.1 V pk	
Oscillator(+/- 2%)(Internal Generator - Charge Mode)	100 pC pk	100 pC pk	
Oscillator(+/- 2%)	100/1000 Hz	100/1000 Hz	
Overload Threshold(± 0.5 Vpk)	± 10 Vpk	± 10 Vpk	
Physical			SUPPLIED ACCESSORIES: Model 017AXX Power Cord (1) Model EE75 PCB MCSC Control Software. (1)
Electrical Connector(Input, sensor)	BNC Jack	BNC Jack	
Electrical Connector(Output)	BNC Jack	BNC Jack	
Electrical Connector(Ethernet)	RJ-45	RJ-45	
Size (Height x Width x Depth)(nominal)	1.75 in x 19 in x 13.7 in	44.5 mm x 482.6 mm x 348 mm	
Weight	8 lb	3.6 kg	
 [7] All specifications are at room temperature unless otherwise specified. In the interest of constant product improvement, we reserve the right to change specifications without notice.			
 PCB PIEZOTRONICS AN AMPHENOL COMPANY		Phone: 716-684-0001 Fax: 716-684-0987 E-Mail: info@pcb.com	
3425 Walden Avenue, Depew, NY 14043			
Entered: ND	Engineer: CPH	Sales: AH	Approved: JWH
Date: 12/3/2025	Date: 12/3/2025	Date: 12/3/2025	Date: 12/3/2025
46076			